

EASY DESIGN™ GUIDE

What is Easy Design?

1
Select the correct type of speaker for the job
(see chart below)

2
Find the number of speakers needed
(see charts on pages 4-6)

3
Select the amplifier for the system
(see page 7)

Armed with just 3 pieces of information, you can quickly create a bill of material for speaker paging jobs. Bogen's Easy Design line of products was created specifically to make the design process easier and less time consuming for the installer.

You supply some basic pieces of information – type of application, dimensions of the area to be covered, ambient noise level, and ceiling height*. Then, a few simple and direct charts will immediately provide you with the best type of speaker to use, the number of speakers needed, and the amplifier size required for the job.

Each speaker in the Easy Design line is designed with a single power tap and a volume control. Any paging system you create using the Easy Design products will be flexible, robust, and powerful. If noise levels increase in the future, just turn up the volume controls on the speakers – the amplifier will not overload!

You get all the benefits of a 70V central-amplified system – full power capability, high-quality sound and performance, 2-wire installation, long speaker runs, flexibility in amplifier location, no distributed power supplies – and now, super simple system design (we've eliminated the multiple power taps). Easy Design speakers have the high quality and reliability you expect from Bogen.

* Not all dimensions needed for all speaker types. Refer to section 2 for specific dimensions needed for each speaker.

1 Select Speaker Type

- Determine the **ambient noise level and type of environment** in which the speakers will be installed.
- Then select the **speaker(s) best suited** for the area.

Example:

- The ambient noise level in a machine shop in an industrial area is 90 dB. By referring to the chart, you will find that the HS30EZ horn loudspeaker is best suited for this environment.

For applications with mixed noise levels, such as a location with quiet waiting rooms, medium noise level office areas, and very noisy manufacturing, select an appropriate speaker type for each different area.

Once you have selected the speaker type(s), the next step is to determine how many speakers you will need to cover the area sufficiently.

SPEAKER MODELS		SM1EZ WB1EZ CS1EZ <i>see chart on pages 4 & 6</i>	HS7EZ <i>see chart on page 5</i>	HS15EZ HS30EZ <i>see chart on page 5</i>
TYPICAL AMBIENT NOISE LEVEL	TYPICAL ENVIRONMENTS			
VERY HIGH NOISE 85-95 dB <i>Speech Almost Impossible To Hear</i>	<ul style="list-style-type: none"> • Construction Site • Loud Machine Shop • Noisy Manufacturing • Printing Shop 			
HIGH NOISE 75-85 dB <i>Speech Is Difficult To Hear</i>	<ul style="list-style-type: none"> • Assembly Line • Crowded Transit Waiting Area • Machine/Print Shop • Shipping Warehouse • Supermarket (Peak) • Very Noisy Bar or Restaurant 			
MEDIUM NOISE 65-75 dB <i>Must Raise Voice To Be Heard</i>	<ul style="list-style-type: none"> • Bank/Public Area • Transit Waiting Area • Department Store • Noisy Office Setting • Supermarket (Normal) • Bar or Restaurant 			
LOW NOISE 55-65 dB <i>Speech Is Easy To Hear</i>	<ul style="list-style-type: none"> • Conversational Speech • Doctor's Office • Hospital • Hotel Lobby • Quiet Office • Quiet Bar or Restaurant 			

*For applications over 100 dB, contact Bogen for assistance.

EASY DESIGN™ GUIDE (cont.)

2 Determine the Number of Speakers Needed



CS1EZ



SM1EZ

CS1EZ Ceiling Speaker SM1EZ Surface-Mount Ceiling Speaker

Use this chart to determine the number of CS1EZ Ceiling Speakers and/or SM1EZ Surface-Mount Ceiling Speakers a particular installation will require, based on the dimensions of the area and the ceiling height.

RED for 8' Ceiling
BLUE for 10' Ceiling
GREEN for 12' Ceiling

Look Up LONGER Dimension Of Area On This Side

	20	30	40	50	60	70	80	90	100	110	120	130	140	150	160	170	180	190	200
20	1	2	3	4	5	6	6	7	8	9	10	10	11	12	13	13	14	15	16
30	1	2	2	3	3	4	4	5	5	6	6	7	7	8	8	9	9	10	10
40	1	1	2	2	2	3	3	3	4	4	4	5	5	5	6	6	6	7	7
50	2	3	4	5	5	6	6	7	8	8	9	10	11	11	12	13	14	14	15
60	2	2	3	3	4	4	4	5	5	6	6	7	7	8	8	9	9	10	11
70	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20	21
80	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20	21	22
90	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20	21	22
100	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20	21	22	23
110	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20	21	22	23
120	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20	21	22	23	24
130	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20	21	22	23	24
140	7	8	9	10	11	12	13	14	15	16	17	18	19	20	21	22	23	24	25
150	7	8	9	10	11	12	13	14	15	16	17	18	19	20	21	22	23	24	25
160	8	9	10	11	12	13	14	15	16	17	18	19	20	21	22	23	24	25	26
170	8	9	10	11	12	13	14	15	16	17	18	19	20	21	22	23	24	25	26
180	9	10	11	12	13	14	15	16	17	18	19	20	21	22	23	24	25	26	27
190	9	10	11	12	13	14	15	16	17	18	19	20	21	22	23	24	25	26	27
200	10	11	12	13	14	15	16	17	18	19	20	21	22	23	24	25	26	27	28

Look Up SHORTER Dimension Of Area On This Side

Ceiling Speakers (CS1EZ, SM1EZ)

- Obtain the length, width, and ceiling height of the area.
- Look up where the **length** and **width** of the area meet on the chart.
- You will find three color-coded numbers. Use the **red** number for 8 ft. ceilings, **blue** for 10 ft. ceilings, and **green** for 12 ft. ceilings. The color-coded number that corresponds to the area's **ceiling height** is the general number of speakers the installation requires.


The **minimum amplifier power** needed (in watts) is equal to the total number of CS1EZ or SM1EZ speakers required in the area for uniform coverage.

Amplifier Power (min.) = Number of CS1EZ or SM1EZ Speakers

Example:

An office area, using CS1EZ Ceiling Speakers (or SM1EZ Surface-Mount Ceiling Speakers), is 100 feet long by 70 feet wide by 10 feet high. Crisscross the length (100 feet) and width (70 feet) on the chart. You will find three color-coded numbers: 27, 18, and 12. Since blue numbers are used for ceiling heights of 10 feet, 18 is the recommended quantity of CS1EZ speakers needed for this application. This number - 18 - is also the minimum amplifier power needed (in watts) for this area.

NOW, TURN TO PAGE 7 TO SELECT AMPLIFIER.



Horn Loudspeakers (HS7EZ, HS15EZ, HS30EZ)

- Obtain the **square footage** of the area to be covered and its ambient noise level.
- Where the area's square footage intersects the area's **ambient noise level**, you will find two numbers.

The number in **blue** is the typical number of horn loudspeakers the installation requires. Additional speakers may be needed in areas that have obstructions, like shelving, that block sound dispersion.

The number in **red** is the minimum amplifier power needed (in watts) for the installation.

Amplifier Power (min.) = Number in Red

Example:

A factory has 35,000 square feet of open area and an average ambient noise level of 80 dB. Thus, it will require HS15EZ Horn Loudspeakers. Using the chart for the HS15EZ speaker, crisscross the square footage and the ambient noise level. The number of horn loudspeakers needed with an installation is shown in blue and the minimum amplifier power for this number of speakers is shown in red. As you can see, 6 speakers are needed for this application and the minimum amplifier power needed is 90 watts.

HS7EZ Horn Loudspeaker



Use this chart to determine the number of HS7EZ Horn Loudspeakers a particular installation will require, based on the size of the area and the ambient noise level of the environment.

HORN QTY. & MIN. POWER (WATTS) BASED ON AMBIENT NOISE	SIZE OF AREA TO BE COVERED (THOUSANDS OF SQUARE FEET)																			
	5	10	15	20	25	30	35	40	45	50	55	60	65	70	75	80	85	90	95	100
55-65 dB Low Noise – speech is easy	1	1	2	2	3	3	4	4	5	5	6	6	7	7	8	8	9	9	10	10
	8	8	15	15	23	23	30	30	38	38	45	45	53	53	60	60	68	68	75	75
65-75 dB Medium Noise – must raise voice to be heard	1	2	3	4	5	5	6	7	8	9	10	10	11	12	13	14	15	15	16	17
	8	15	23	30	38	38	45	53	60	68	75	75	83	90	98	105	113	113	120	128

The # in **blue** is the # of speakers.

The # in **red** is the minimum amplifier power required.

NOW, TURN TO PAGE 7 TO SELECT AMPLIFIER.

HS15EZ Horn Loudspeaker



Use this chart to determine the number of HS15EZ Horn Loudspeakers a particular installation will require, based on the size of the area and the ambient noise level of the environment.

HORN QTY. & MIN. POWER (WATTS) BASED ON AMBIENT NOISE	SIZE OF AREA TO BE COVERED (THOUSANDS OF SQUARE FEET)																			
	5	10	15	20	25	30	35	40	45	50	55	60	65	70	75	80	85	90	95	100
75-85 dB High Noise – speech is difficult	1	2	3	4	5	5	6	7	8	9	10	10	11	12	13	14	15	15	16	17
	15	30	45	60	75	75	90	105	120	135	150	150	165	180	195	210	225	225	240	255
85-95 dB Very High Noise – speech almost impossible	2	4	6	8	10	12	14	16	18	20	22	24	26	28	30	32	34	36	38	40
	30	60	90	120	150	180	210	240	270	300	330	360	390	420	450	480	510	540	570	600

The # in **blue** is the # of speakers.

The # in **red** is the minimum amplifier power required.

NOW, TURN TO PAGE 7 TO SELECT AMPLIFIER.

HS30EZ Horn Loudspeaker



Use this chart to determine the number of HS30EZ Horn Loudspeakers a particular installation will require, based on the size of the area and the ambient noise level of the environment.

For Applications over 100 dB, Contact Bogen for Assistance.

HORN QTY. & MIN. POWER (WATTS) BASED ON AMBIENT NOISE	SIZE OF AREA TO BE COVERED (THOUSANDS OF SQUARE FEET)																			
	5	10	15	20	25	30	35	40	45	50	55	60	65	70	75	80	85	90	95	100
85-95 dB Very High Noise – speech almost impossible	1	2	3	4	6	7	8	9	10	11	12	13	14	16	17	18	19	20	21	22
	30	60	90	120	180	210	240	270	300	330	360	390	420	480	510	540	570	600	630	660

The # in **blue** is the # of speakers.

The # in **red** is the minimum amplifier power required.

NOW, TURN TO PAGE 7 TO SELECT AMPLIFIER.

EASY DESIGN™ GUIDE (cont.)

2 Determine the Number of Speakers Needed (cont.)



WB1EZ Wall Baffle Speaker

Use this chart to determine the number of **WB1EZ** speakers a particular installation will require, based on the dimensions of the area.

Look Up LONGER Dimension Of Area On This Side

	20	30	40	50	60	70	80	90	100	110	120	130	140	150	160	170	180	190	200
20	1	1	1	2	2	2	3	3	3	4	4	4	5	5	5	6	6	6	6
30	2	2	3	3	4	4	5	5	6	6	7	7	8	8	9	9	10	10	10
40	3	3	4	5	5	6	7	7	8	9	9	10	11	11	12	12	13	13	13
50	4	5	6	7	8	8	9	10	11	12	12	13	14	15	16	17	17	18	18
60	6	7	8	9	10	11	12	13	14	15	16	18	19	20	21	22	23	23	24
70	8	9	11	12	13	14	15	16	17	19	20	21	23	24	25	27	27	28	29
80	11	12	13	15	16	17	19	20	21	23	25	27	28	30	32	33	34	35	37
90	14	15	16	18	20	21	23	24	26	27	28	30	32	33	35	37	38	40	41
100	17	18	20	22	23	25	27	28	30	32	33	35	37	39	42	44	44	46	48
110	20	22	24	26	28	29	31	33	35	37	39	42	45	47	49	51	53	55	57
120	24	26	28	30	32	34	36	38	40	43	45	48	51	53	56	59	61	64	66
130	28	30	33	35	37	39	42	44	47	50	53	56	59	62	65	68	71	74	77
140	33	35	37	40	42	45	47	50	53	56	59	62	65	68	71	74	77	80	83
150	33	40	43	45	48	51	54	57	60	63	66	69	72	75	78	81	84	87	90
160	43	45	48	51	54	57	60	63	66	69	72	75	78	81	84	87	90	93	96
170	48	52	54	56	59	62	65	68	71	74	77	80	83	86	89	92	95	98	101
180	54	58	60	63	66	69	72	75	78	81	84	87	90	93	96	99	102	105	108
190	60	64	66	69	72	75	78	81	84	87	90	93	96	99	102	105	108	111	114
200	66	70	72	75	78	81	84	87	90	93	96	99	102	105	108	111	114	117	120

Look Up SHORTER Dimension Of Area On This Side

Wall Baffle Speaker (WB1EZ)

- Obtain the **length** and **width** of the area.
- Where the length and width of the area crisscross on the chart, you will find the typical **number of speakers** that the installation requires.

The **minimum amplifier power** needed (*in watts*) is equal to the total number of WB1EZ speakers required in the area for uniform coverage.

Amplifier Power (min.) = Number of WB1EZ Speakers

Example:

An area's dimensions are 150 ft. long by 110 ft. wide. Crisscross these two dimensions on the chart and you will find that 28 WB1EZ Wall Baffle Speakers are needed for this application. This number – 28 – is also the minimum amplifier power needed (*in watts*) for this area.

Mixed Speaker Type Applications

For applications with more than one type of speaker:

- Determine the number of speakers and the minimum amplifier power needed for each type of speaker separately.
- Add together the minimum amplifier power needed for each type of speaker to obtain the minimum amplifier power needed for the entire application.

Example:

An application requires 10 SM1EZ Surface-Mount Ceiling Speakers (*minimum amplifier power needed is 10 watts*), 5 HS15EZ Horn Loudspeakers (*minimum amplifier power needed is 75 watts*), and 10 WB1EZ Wall Baffle Speakers (*minimum amplifier power needed is 10 watts*). Add together the minimum amplifier power needed for each type of speaker: 10 watts + 75 watts + 10 watts. The sum is 95 watts. This is the minimum amplifier power needed (*in watts*) for the entire application.

NOW, GO TO PAGE 7 TO SELECT AMPLIFIER.

3 Select An Amplifier

Once you determine the number of speakers and the minimum amplifier power for the installation, you are ready to select the system amplifier. A 70V paging amplifier is very easy to select.

- Locate amplifiers on the chart that have a **wattage equal to or higher** than the minimum amplifier power of your application. (Amplifiers with power capacities greater than this number will not damage the speakers. The extra power available is simply not used.)
- Determine the **amplifier features** needed for the application (see the Site Survey Check List on page 72 and the Amplifier Features Chart on page 78).
- Using the chart on page 78, **find an amplifier** that offers these features. As long as the wattage of the selected amplifier is equal to or higher than the minimum amplifier power, the amplifier will work well for the application.

If you think the application's system may need to expand in the future (this is often the case with new constructions and relocating companies), you may want to select an amplifier with a greater power capacity now.

Example:

An application requiring 18 CS1EZ Ceiling Speakers requires a minimum amplifier power of 18 watts, so an amplifier with a power rating of 18 watts minimum is needed. Now, look at the chart on page 78 to determine which amplifiers provide the necessary wattage to drive the speakers as well as provide the amplifier features that are most appropriate for the installation. Since the minimum wattage needed is 18, the amplifier with the lowest power usable for this installation is 20 watts (model C20). However, if the C20 does not have the features required for the application, such as bass and treble controls, you can select any amplifier of greater wattage that offers the specific features. For instance, you might select the TPU35B or C35. Both of these amplifiers have a higher wattage than the application's minimum amplifier power needed and provide the desired features because they have bass and treble controls. Either of these amplifiers will work well for this application. Plus, there is room to expand the system on a 35W or higher amplifier without the need to purchase an additional amplifier in the future.

The Amplifier Features Chart outlines the features and power ratings of Bogen amplifiers that can be used for a variety of application needs. For complete chart, see page 78.

A POWER

Locate a power rating that is higher than the application requires (allowing for future system expansion).

B FEATURES

Find the amplifier features that the application requires.

Amplifier Power Rating/Channel	Model Numbers	Input Types				Signal Processing				Music Mating				Mounting			Page Number						
		100 Input* 100V/200V	Mic Inputs* 1/2" Balanced	Aux Inputs* 1/2" Unbalanced	Balanced Inputs 1/2"	Modular Inputs	Alpha Aural Exciter	Leadless Controller	ALC	EQ	Bass/Treble	Tone Control	Variable Mute	Auto Mute	Manual Mute	MTX Output		Night Ringer	Remote Volume	Display Volume	Wall Mount	Shelf Mount	Rack Mount
1.5W	GA2	1																					40
5W	GMA	1	1	1																			40
10W	C10	1	1	2 (1)	0 (1)																		40
10W	C10MDH	1	1	2 (1)	0 (1)																		40
15W	TPU15A	1	1		1																		44
20W	C20	1	1	2 (1)	0 (1)																		40
20W	C20MDH	1	1	2 (1)	0 (1)																		40
35W	C35	1	1	2 (1)	1 (2)																		40
35W	GS35	1	1 (1)	1 (1)	1 (2)																		39
35W	TPU35B	1	1	1	1																		44
35W	C35	1	1	1	1																		36
60W	MP60	1																					41
60W	C60			1 (2)																			40

C MODEL NUMBER

Select the amplifier model(s) best suited for your application.

D REFERENCE PAGE

Turn to the page number indicated for more information about the product you need.

REFER TO CHART ON PAGE 78

Easy Design™ Is Easy!

That's all it takes to design a robust, high-quality paging system with Bogen's Easy Design line.